

Product summary

- The TY-FB11DTA, terminal board type digital tuner saves space.
- The TY-FB11DTA has HDMI input terminal, Video and audio output terminals that enables the display to connect other video sources.
(The video output terminal is supported by the antenna input signals only)
- Optical digital audio output terminal supports 5.1ch Speaker System .
- An optional SD memory card allows to use the clone function which allows programmed memories and settings from one tuner to be transferred to other tuners.

Product specification (design and specification subject to change without notice)

Slot Compatibility	
3 Slot model	Slot 2, Slot 3 (Slot 1 is not compatible)
Receiving Systems	
DVB-T	7MHz VHF / UHF (Australia) free-to-air TV broadcast reception
Connectional Terminals	
AV IN HDMI	TYPE A Connector
DIGITAL AUDIO OUT	PCM / Dolby Digital, Fiber optic
VIDEO OUT	RCA PIN Type 1.0 V [p-p] (75 Ω)
AUDIO OUT	M3 PIN Type L-R 0.5 V [rms]
Ir System	Ir System or though out (Setting selected using the DIP switches)
SD Card Slot	Used for servicing
Weight	
	approx. 600 g
Included Accessories	
	Remote control x 1, Remote control batteries R6(AA) x 2, Terminal function label x 1, Ir System cable x 1, Screw x 4
Dimensions	

Cautions: This drawing is not a scale.

Units : mm

